



#1032

### ARCHITECTS' AND ENGINEERS' SPECIFICATIONS

The Emergency Strobe and Indicator Light(s) shall be Alpha Communications®/Stento model #1032 or approved equivalent.

The strobe(s) shall produce 1.0 million candlepower (strobe) and 6 candela (fluorescent). The strobe(s) shall be made of a vandal-resistant polycarbonate dome, and shall be available in the following colors; Blue (standard) or Red, Yellow, Green or Clear (optional). The strobe(s) shall be weather-resistant and can be used directly outdoors. The strobe is designed to be used with a Stento emergency-call intercom system.

Each #1032 strobe shall require a model #9689 strobe control relay board for proper operation.

Contractor shall observe all local and national electrical codes.

### #1032 Emergency Strobe and Indicator Light

The #1032 is a combination strobe (1 million candlepower) and 7 watt fluorescent indicator light that is contained in a weather tight and vandal resistant polycarbonate dome.

The unit provides leads capable of activating the strobe when connected to a contact closure and works with emergency intercom units for both the constant on and emergency strobe functions.

The 1032 strobe mounts to a 2-gang surface/bell box with optional strobe bracket #1033. The strobe is ideal when used with the #9625 and #62926 intercom remote stations. Each 1032 strobe requires a model #9689 Strobe Control Relay Board. The 1032 dome is available in standard Blue, or optional Red, Yellow, Green or Clear.

### FEATURES

- Available in standard Blue, or optional Red, Yellow, Green or Clear
- Vandal-resistant Polycarbonate Dome
- 1 Million Candlepower Strobe
- 7 Watt Fluorescent Light
- Simple to Install
- Weather-Resistant for Outdoor Use

### SPECIFICATIONS

<b>Dimensions:</b>	6.125"H x 5.53"W (156mm x 141mm)
<b>Input Voltage:</b>	90VAC - 132VAC
<b>Operating Volt.:</b>	18 volts max.
<b>Operating Curr.:</b>	5 mA max.
<b>Operating Temp.:</b>	-30 degrees C to +60 degrees C (22F degrees to 140 degrees F)
<b>Operating Hum.:</b>	0 to 95%
<b>Candlepower (strobe):</b>	1.0 million
<b>Candlepower (fluorescent):</b>	6 candela

*Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice.*